

**MX3000R**

Barcode: 9356905000012

# 3.5kVA PETROL GENERATOR

4 STAGE DIGITAL METER | AUTOMATIC VOLTAGE REGULATOR  
SUPERIOR QUALITY SENCI ALTERNATOR

- > 4 Stage Digital Meter Display
- > Automatic Voltage Regulator
- > Low Oil Alert Sensor
- > Superior Quality SENCI Alternator
- > 15L Capacity Fuel Tank
- > Large Muffler Design to Reduce Noise
- > Heavy Duty 25mm Frame



Voltage (V)	240V
Amperage (A)	10.4A
Displacement (cc)	208cc
Fuel Tank Capacity (L)	15L
Rated Power (Watts)	3.1kVA/2500W
Max. Power (Watts)	3.5kVA/2800W

Noise Level (dB's) at 7m @ 75% Load	77
Weight (Net)	48kg
Ignition	Manual/Recoil
Rated Frequency	50Hz
Cont. Running Time @50% Load	9 hrs
Cont. Running Time @100% Load	6.5 hrs



- Generator Dimensions  
Length 589mm | Width 438mm | Height 540mm | Weight 41kg
- Box Dimensions  
Length 605mm | Width 505mm | Height 575mm | Weight 44kg